
PROAUDIO

Lavalier condenser microphone

P966L

User Manual



Congratulation for choosing a PROAUDIO® product.
Please read the instruction manual carefully before use.

Lavalier condenser microphone P966L

PROAUDIO® presents a line of microphones suitable for the different recording situations. Quality, reliability and above all, precision in the sound recording, are the main features that make this series an essential reference point for the sound recording professional.

P966L is a lavalier condenser microphone with cardioid polar pattern designed for TV shows and conferences.



- Great transparency that grants an high speech intelligibility
- Suitable also for acoustic instruments
- Wide dynamic range and frequency response for excellent sound reinforcement
- Small size for minimum visibility
- Together with clothing clip for easy attaching to a tie, lapel, dress etc.
- Connection: 4 poles mini XLR
- Cable length: 1,2 mt

Specifications

Polar pattern	Cardioid
Element	Pressure gradient FET preamplifier
Frequency response	100-15,000Hz
Impedance	2.2K Ω \pm 30%
Max. SPL	130dB
Signal-to-noise ratio	55 dB
Power supply	Phantom power 1.5-10V DC
Current consumption	3.5mA
Connector	Mini XLR connector
Dimensions (Capsule)	12 x 31 x 12 mm
Weight (including clip)	28 g



Lavalier condenser microphone

P966L

